



**NRC06FxxxxTR 0603 Size**

**Thick Film Chip Resistor Marking Guide**

**3-Digit Marking Codes for +/-1% (F) tolerance E96 Values**

RESISTANCE VALUE	NIC P/N	3 DIGIT MARKING
10.0 Ohm	NRC06F10R0TR	01X
10.2 Ohm	NRC06F10R2TR	02X
10.5 Ohm	NRC06F10R5TR	03X
10.7 Ohm	NRC06F10R7TR	04X
11.0 Ohm	NRC06F11R0TR	05X
11.3 Ohm	NRC06F11R3TR	06X
11.5 Ohm	NRC06F11R5TR	07X
11.8 Ohm	NRC06F11R8TR	08X
12.1 Ohm	NRC06F12R1TR	09X
12.4 Ohm	NRC06F12R4TR	10X
12.7 Ohm	NRC06F12R7TR	11X
13.0 Ohm	NRC06F13R0TR	12X
13.3 Ohm	NRC06F13R3TR	13X
13.7 Ohm	NRC06F13R7TR	14X
14.0 Ohm	NRC06F14R0TR	15X
14.3 Ohm	NRC06F14R3TR	16X
14.7 Ohm	NRC06F14R7TR	17X
15.0 Ohm	NRC06F15R0TR	18X
15.4 Ohm	NRC06F15R4TR	19X
15.8 Ohm	NRC06F15R8TR	20X
16.2 Ohm	NRC06F16R2TR	21X
16.5 Ohm	NRC06F16R5TR	22X
16.9 Ohm	NRC06F16R9TR	23X
17.4 Ohm	NRC06F17R4TR	24X
17.8 Ohm	NRC06F17R8TR	25X
18.2 Ohm	NRC06F18R2TR	26X
18.7 Ohm	NRC06F18R7TR	27X
19.1 Ohm	NRC06F19R1TR	28X
19.6 Ohm	NRC06F19R6TR	29X
20.0 Ohm	NRC06F20R0TR	30X
20.5 Ohm	NRC06F20R5TR	31X
21.0 Ohm	NRC06F21R0TR	32X
21.5 Ohm	NRC06F21R5TR	33X
22.1 Ohm	NRC06F22R1TR	34X
22.6 Ohm	NRC06F22R6TR	35X
23.2 Ohm	NRC06F23R2TR	36X

**NIC COMPONENTS CORP.**

[www.nicccomp.com](http://www.nicccomp.com)

23.7 Ohm	NRC06F23R7TR	<b>37X</b>
24.3 Ohm	NRC06F24R3TR	<b>38X</b>
24.9 Ohm	NRC06F24R9TR	<b>39X</b>
25.5 Ohm	NRC06F25R5TR	<b>40X</b>
26.1 Ohm	NRC06F26R1TR	<b>41X</b>
26.7 Ohm	NRC06F26R7TR	<b>42X</b>
27.4 Ohm	NRC06F27R4TR	<b>43X</b>
28.0 Ohm	NRC06F28R0TR	<b>44X</b>
28.7 Ohm	NRC06F28R7TR	<b>45X</b>
29.4 Ohm	NRC06F29R4TR	<b>46X</b>
30.1 Ohm	NRC06F30R1TR	<b>47X</b>
30.9 Ohm	NRC06F30R9TR	<b>48X</b>
31.6 Ohm	NRC06F31R6TR	<b>49X</b>
32.4 Ohm	NRC06F32R4TR	<b>50X</b>
33.2 Ohm	NRC06F33R2TR	<b>51X</b>
34.0 Ohm	NRC06F34R0TR	<b>52X</b>
34.8 Ohm	NRC06F34R8TR	<b>53X</b>
35.7 Ohm	NRC06F35R7TR	<b>54X</b>
36.5 Ohm	NRC06F36R5TR	<b>55X</b>
37.4 Ohm	NRC06F37R4TR	<b>56X</b>
38.3 Ohm	NRC06F38R3TR	<b>57X</b>
39.2 Ohm	NRC06F39R2TR	<b>58X</b>
40.2 Ohm	NRC06F40R2TR	<b>59X</b>
41.2 Ohm	NRC06F41R2TR	<b>60X</b>
42.2 Ohm	NRC06F42R2TR	<b>61X</b>
43.2 Ohm	NRC06F43R2TR	<b>62X</b>
44.2 Ohm	NRC06F44R2TR	<b>63X</b>
45.3 Ohm	NRC06F45R3TR	<b>64X</b>
46.4 Ohm	NRC06F46R4TR	<b>65X</b>
47.5 Ohm	NRC06F47R5TR	<b>66X</b>
48.7 Ohm	NRC06F48R7TR	<b>67X</b>
49.9 Ohm	NRC06F49R9TR	<b>68X</b>
51.1 Ohm	NRC06F51R1TR	<b>69X</b>
52.3 Ohm	NRC06F52R3TR	<b>70X</b>
53.6 Ohm	NRC06F53R6TR	<b>71X</b>
54.9 Ohm	NRC06F54R9TR	<b>72X</b>
56.2 Ohm	NRC06F56R2TR	<b>73X</b>
57.6 Ohm	NRC06F57R6TR	<b>74X</b>
59.0 Ohm	NRC06F59R0TR	<b>75X</b>
60.4 Ohm	NRC06F60R4TR	<b>76X</b>
61.9 Ohm	NRC06F61R9TR	<b>77X</b>
63.4 Ohm	NRC06F63R4TR	<b>78X</b>

**NIC COMPONENTS CORP.**

[www.nicccomp.com](http://www.nicccomp.com)

64.9 Ohm	NRC06F64R9TR	<b>79X</b>
66.5 Ohm	NRC06F66R5TR	<b>80X</b>
68.1 Ohm	NRC06F68R1TR	<b>81X</b>
69.8 Ohm	NRC06F69R8TR	<b>82X</b>
71.5 Ohm	NRC06F71R5TR	<b>83X</b>
73.2 Ohm	NRC06F73R2TR	<b>84X</b>
75.0 Ohm	NRC06F75R0TR	<b>85X</b>
76.8 Ohm	NRC06F76R8TR	<b>86X</b>
78.7 Ohm	NRC06F78R7TR	<b>87X</b>
80.6 Ohm	NRC06F80R6TR	<b>88X</b>
82.5 Ohm	NRC06F82R5TR	<b>89X</b>
84.5 Ohm	NRC06F84R5TR	<b>90X</b>
86.6 Ohm	NRC06F86R6TR	<b>91X</b>
88.7 Ohm	NRC06F88R7TR	<b>92X</b>
90.9 Ohm	NRC06F90R9TR	<b>93X</b>
93.1 Ohm	NRC06F93R1TR	<b>94X</b>
95.3 Ohm	NRC06F95R3TR	<b>95X</b>
97.6 Ohm	NRC06F97R6TR	<b>96X</b>
100 Ohm	NRC06F1000TR	<b>01A</b>
102 Ohm	NRC06F1020TR	<b>02A</b>
105 Ohm	NRC06F1050TR	<b>03A</b>
107 Ohm	NRC06F1070TR	<b>04A</b>
110 Ohm	NRC06F1100TR	<b>05A</b>
113 Ohm	NRC06F1130TR	<b>06A</b>
115 Ohm	NRC06F1150TR	<b>07A</b>
118 Ohm	NRC06F1180TR	<b>08A</b>
121 Ohm	NRC06F1210TR	<b>09A</b>
124 Ohm	NRC06F1240TR	<b>10A</b>
127 Ohm	NRC06F1270TR	<b>11A</b>
130 Ohm	NRC06F1300TR	<b>12A</b>
133 Ohm	NRC06F1330TR	<b>13A</b>
137 Ohm	NRC06F1370TR	<b>14A</b>
140 Ohm	NRC06F1400TR	<b>15A</b>
143 Ohm	NRC06F1430TR	<b>16A</b>
147 Ohm	NRC06F1470TR	<b>17A</b>
150 Ohm	NRC06F1500TR	<b>18A</b>
154 Ohm	NRC06F1540TR	<b>19A</b>
158 Ohm	NRC06F1580TR	<b>20A</b>
162 Ohm	NRC06F1620TR	<b>21A</b>
165 Ohm	NRC06F1650TR	<b>22A</b>
169 Ohm	NRC06F1690TR	<b>23A</b>
174 Ohm	NRC06F1740TR	<b>24A</b>

**NIC COMPONENTS CORP.**

[www.nicccomp.com](http://www.nicccomp.com)

178 Ohm	NRC06F1780TR	<b>25A</b>
182 Ohm	NRC06F1820TR	<b>26A</b>
187 Ohm	NRC06F1870TR	<b>27A</b>
191 Ohm	NRC06F1910TR	<b>28A</b>
196 Ohm	NRC06F1960TR	<b>29A</b>
200 Ohm	NRC06F2000TR	<b>30A</b>
205 Ohm	NRC06F2050TR	<b>31A</b>
210 Ohm	NRC06F2100TR	<b>32A</b>
215 Ohm	NRC06F2150TR	<b>33A</b>
221 Ohm	NRC06F2210TR	<b>34A</b>
226 Ohm	NRC06F2260TR	<b>35A</b>
232 Ohm	NRC06F2320TR	<b>36A</b>
237 Ohm	NRC06F2370TR	<b>37A</b>
243 Ohm	NRC06F2430TR	<b>38A</b>
249 Ohm	NRC06F2490TR	<b>39A</b>
255 Ohm	NRC06F2550TR	<b>40A</b>
261 Ohm	NRC06F2610TR	<b>41A</b>
267 Ohm	NRC06F2670TR	<b>42A</b>
274 Ohm	NRC06F2740TR	<b>43A</b>
280 Ohm	NRC06F2800TR	<b>44A</b>
287 Ohm	NRC06F2870TR	<b>45A</b>
294 Ohm	NRC06F2940TR	<b>46A</b>
301 Ohm	NRC06F3010TR	<b>47A</b>
309 Ohm	NRC06F3090TR	<b>48A</b>
316 Ohm	NRC06F3160TR	<b>49A</b>
324 Ohm	NRC06F3240TR	<b>50A</b>
332 Ohm	NRC06F3320TR	<b>51A</b>
340 Ohm	NRC06F3400TR	<b>52A</b>
348 Ohm	NRC06F3480TR	<b>53A</b>
357 Ohm	NRC06F3570TR	<b>54A</b>
365 Ohm	NRC06F3650TR	<b>55A</b>
374 Ohm	NRC06F3740TR	<b>56A</b>
383 Ohm	NRC06F3830TR	<b>57A</b>
392 Ohm	NRC06F3920TR	<b>58A</b>
402 Ohm	NRC06F4020TR	<b>59A</b>
412 Ohm	NRC06F4120TR	<b>60A</b>
422 Ohm	NRC06F4220TR	<b>61A</b>
432 Ohm	NRC06F4320TR	<b>62A</b>
442 Ohm	NRC06F4420TR	<b>63A</b>
453 Ohm	NRC06F4530TR	<b>64A</b>
464 Ohm	NRC06F4640TR	<b>65A</b>
475 Ohm	NRC06F4750TR	<b>66A</b>

**NIC COMPONENTS CORP.**

[www.nicccomp.com](http://www.nicccomp.com)

487 Ohm	NRC06F4870TR	<b>67A</b>
499 Ohm	NRC06F4990TR	<b>68A</b>
511 Ohm	NRC06F5110TR	<b>69A</b>
523 Ohm	NRC06F5230TR	<b>70A</b>
536 Ohm	NRC06F5360TR	<b>71A</b>
549 Ohm	NRC06F5490TR	<b>72A</b>
562 Ohm	NRC06F5620TR	<b>73A</b>
576 Ohm	NRC06F5760TR	<b>74A</b>
590 Ohm	NRC06F5900TR	<b>75A</b>
604 Ohm	NRC06F6040TR	<b>76A</b>
619 Ohm	NRC06F6190TR	<b>77A</b>
634 Ohm	NRC06F6340TR	<b>78A</b>
649 Ohm	NRC06F6490TR	<b>79A</b>
665 Ohm	NRC06F6650TR	<b>80A</b>
681 Ohm	NRC06F6810TR	<b>81A</b>
698 Ohm	NRC06F6980TR	<b>82A</b>
715 Ohm	NRC06F7150TR	<b>83A</b>
732 Ohm	NRC06F7320TR	<b>84A</b>
750 Ohm	NRC06F7500TR	<b>85A</b>
768 Ohm	NRC06F7680TR	<b>86A</b>
787 Ohm	NRC06F7870TR	<b>87A</b>
806 Ohm	NRC06F8060TR	<b>88A</b>
825 Ohm	NRC06F8250TR	<b>89A</b>
845 Ohm	NRC06F8450TR	<b>90A</b>
866 Ohm	NRC06F8660TR	<b>91A</b>
887 Ohm	NRC06F8870TR	<b>92A</b>
909 Ohm	NRC06F9090TR	<b>93A</b>
931 Ohm	NRC06F9310TR	<b>94A</b>
953 Ohm	NRC06F9530TR	<b>95A</b>
976 Ohm	NRC06F9760TR	<b>96A</b>
1000 Ohm	NRC06F1001TR	<b>01B</b>
1020 Ohm	NRC06F1021TR	<b>02B</b>
1050 Ohm	NRC06F1051TR	<b>03B</b>
1070 Ohm	NRC06F1071TR	<b>04B</b>
1100 Ohm	NRC06F1101TR	<b>05B</b>
1130 Ohm	NRC06F1131TR	<b>06B</b>
1150 Ohm	NRC06F1151TR	<b>07B</b>
1180 Ohm	NRC06F1181TR	<b>08B</b>
1210 Ohm	NRC06F1211TR	<b>09B</b>
1240 Ohm	NRC06F1241TR	<b>10B</b>
1270 Ohm	NRC06F1271TR	<b>11B</b>
1300 Ohm	NRC06F1301TR	<b>12B</b>

**NIC COMPONENTS CORP.**

[www.nicccomp.com](http://www.nicccomp.com)

1330 Ohm	NRC06F1331TR	<b>13B</b>
1370 Ohm	NRC06F1371TR	<b>14B</b>
1400 Ohm	NRC06F1401TR	<b>15B</b>
1430 Ohm	NRC06F1431TR	<b>16B</b>
1470 Ohm	NRC06F1471TR	<b>17B</b>
1500 Ohm	NRC06F1501TR	<b>18B</b>
1540 Ohm	NRC06F1541TR	<b>19B</b>
1580 Ohm	NRC06F1581TR	<b>20B</b>
1620 Ohm	NRC06F1621TR	<b>21B</b>
1650 Ohm	NRC06F1651TR	<b>22B</b>
1690 Ohm	NRC06F1691TR	<b>23B</b>
1740 Ohm	NRC06F1741TR	<b>24B</b>
1780 Ohm	NRC06F1781TR	<b>25B</b>
1820 Ohm	NRC06F1821TR	<b>26B</b>
1870 Ohm	NRC06F1871TR	<b>27B</b>
1910 Ohm	NRC06F1911TR	<b>28B</b>
1960 Ohm	NRC06F1961TR	<b>29B</b>
2000 Ohm	NRC06F2001TR	<b>30B</b>
2050 Ohm	NRC06F2051TR	<b>31B</b>
2100 Ohm	NRC06F2101TR	<b>32B</b>
2150 Ohm	NRC06F2151TR	<b>33B</b>
2210 Ohm	NRC06F2211TR	<b>34B</b>
2260 Ohm	NRC06F2261TR	<b>35B</b>
2320 Ohm	NRC06F2321TR	<b>36B</b>
2370 Ohm	NRC06F2371TR	<b>37B</b>
2430 Ohm	NRC06F2431TR	<b>38B</b>
2490 Ohm	NRC06F2491TR	<b>39B</b>
2550 Ohm	NRC06F2551TR	<b>40B</b>
2610 Ohm	NRC06F2611TR	<b>41B</b>
2670 Ohm	NRC06F2671TR	<b>42B</b>
2740 Ohm	NRC06F2741TR	<b>43B</b>
2800 Ohm	NRC06F2801TR	<b>44B</b>
2870 Ohm	NRC06F2871TR	<b>45B</b>
2940 Ohm	NRC06F2941TR	<b>46B</b>
3010 Ohm	NRC06F3011TR	<b>47B</b>
3090 Ohm	NRC06F3091TR	<b>48B</b>
3160 Ohm	NRC06F3161TR	<b>49B</b>
3240 Ohm	NRC06F3241TR	<b>50B</b>
3320 Ohm	NRC06F3321TR	<b>51B</b>
3400 Ohm	NRC06F3401TR	<b>52B</b>
3480 Ohm	NRC06F3481TR	<b>53B</b>
3570 Ohm	NRC06F3571TR	<b>54B</b>

**NIC COMPONENTS CORP.**

[www.nicccomp.com](http://www.nicccomp.com)

3650 Ohm	NRC06F3651TR	<b>55B</b>
3740 Ohm	NRC06F3741TR	<b>56B</b>
3830 Ohm	NRC06F3831TR	<b>57B</b>
3920 Ohm	NRC06F3921TR	<b>58B</b>
4020 Ohm	NRC06F4021TR	<b>59B</b>
4120 Ohm	NRC06F4121TR	<b>60B</b>
4220 Ohm	NRC06F4221TR	<b>61B</b>
4320 Ohm	NRC06F4321TR	<b>62B</b>
4420 Ohm	NRC06F4421TR	<b>63B</b>
4530 Ohm	NRC06F4531TR	<b>64B</b>
4640 Ohm	NRC06F4641TR	<b>65B</b>
4750 Ohm	NRC06F4751TR	<b>66B</b>
4870 Ohm	NRC06F4871TR	<b>67B</b>
4990 Ohm	NRC06F4991TR	<b>68B</b>
5110 Ohm	NRC06F5111TR	<b>69B</b>
5230 Ohm	NRC06F5231TR	<b>70B</b>
5360 Ohm	NRC06F5361TR	<b>71B</b>
5490 Ohm	NRC06F5491TR	<b>72B</b>
5620 Ohm	NRC06F5621TR	<b>73B</b>
5760 Ohm	NRC06F5761TR	<b>74B</b>
5900 Ohm	NRC06F5901TR	<b>75B</b>
6040 Ohm	NRC06F6041TR	<b>76B</b>
6190 Ohm	NRC06F6191TR	<b>77B</b>
6340 Ohm	NRC06F6341TR	<b>78B</b>
6490 Ohm	NRC06F6491TR	<b>79B</b>
6650 Ohm	NRC06F6651TR	<b>80B</b>
6810 Ohm	NRC06F6811TR	<b>81B</b>
6980 Ohm	NRC06F6981TR	<b>82B</b>
7150 Ohm	NRC06F7151TR	<b>83B</b>
7320 Ohm	NRC06F7321TR	<b>84B</b>
7500 Ohm	NRC06F7501TR	<b>85B</b>
7680 Ohm	NRC06F7681TR	<b>86B</b>
7870 Ohm	NRC06F7871TR	<b>87B</b>
8060 Ohm	NRC06F8061TR	<b>88B</b>
8250 Ohm	NRC06F8251TR	<b>89B</b>
8450 Ohm	NRC06F8451TR	<b>90B</b>
8660 Ohm	NRC06F8661TR	<b>91B</b>
8870 Ohm	NRC06F8871TR	<b>92B</b>
9090 Ohm	NRC06F9091TR	<b>93B</b>
9310 Ohm	NRC06F9311TR	<b>94B</b>
9530 Ohm	NRC06F9531TR	<b>95B</b>
9760 Ohm	NRC06F9761TR	<b>96B</b>

**NIC COMPONENTS CORP.**[www.nicccomp.com](http://www.nicccomp.com)

10.0K-Ohm	NRC06F1002TR	<b>01C</b>
10.2K-Ohm	NRC06F1022TR	<b>02C</b>
10.5K-Ohm	NRC06F1052TR	<b>03C</b>
10.7K-Ohm	NRC06F1072TR	<b>04C</b>
11.0K-Ohm	NRC06F1102TR	<b>05C</b>
11.3K-Ohm	NRC06F1132TR	<b>06C</b>
11.5K-Ohm	NRC06F1152TR	<b>07C</b>
11.8K-Ohm	NRC06F1182TR	<b>08C</b>
12.1K-Ohm	NRC06F1212TR	<b>09C</b>
12.4K-Ohm	NRC06F1242TR	<b>10C</b>
12.7K-Ohm	NRC06F1272TR	<b>11C</b>
13.0K-Ohm	NRC06F1302TR	<b>12C</b>
13.3K-Ohm	NRC06F1332TR	<b>13C</b>
13.7K-Ohm	NRC06F1372TR	<b>14C</b>
14.0K-Ohm	NRC06F1402TR	<b>15C</b>
14.3K-Ohm	NRC06F1432TR	<b>16C</b>
14.7K-Ohm	NRC06F1472TR	<b>17C</b>
15.0K-Ohm	NRC06F1502TR	<b>18C</b>
15.4K-Ohm	NRC06F1542TR	<b>19C</b>
15.8K-Ohm	NRC06F1582TR	<b>20C</b>
16.2K-Ohm	NRC06F1622TR	<b>21C</b>
16.5K-Ohm	NRC06F1652TR	<b>22C</b>
16.9K-Ohm	NRC06F1692TR	<b>23C</b>
17.4K-Ohm	NRC06F1742TR	<b>24C</b>
17.8K-Ohm	NRC06F1782TR	<b>25C</b>
18.2K-Ohm	NRC06F1822TR	<b>26C</b>
18.7K-Ohm	NRC06F1872TR	<b>27C</b>
19.1K-Ohm	NRC06F1912TR	<b>28C</b>
19.6K-Ohm	NRC06F1962TR	<b>29C</b>
20.0K-Ohm	NRC06F2002TR	<b>30C</b>
20.5K-Ohm	NRC06F2052TR	<b>31C</b>
21.0K-Ohm	NRC06F2102TR	<b>32C</b>
21.5K-Ohm	NRC06F2152TR	<b>33C</b>
22.1K-Ohm	NRC06F2212TR	<b>34C</b>
22.6K-Ohm	NRC06F2262TR	<b>35C</b>
23.2K-Ohm	NRC06F2322TR	<b>36C</b>
23.7K-Ohm	NRC06F2372TR	<b>37C</b>
24.3K-Ohm	NRC06F2432TR	<b>38C</b>
24.9K-Ohm	NRC06F2492TR	<b>39C</b>
25.5K-Ohm	NRC06F2552TR	<b>40C</b>
26.1K-Ohm	NRC06F2612TR	<b>41C</b>
26.7K-Ohm	NRC06F2672TR	<b>42C</b>

**NIC COMPONENTS CORP.**[www.nicccomp.com](http://www.nicccomp.com)

27.4K-Ohm	NRC06F2742TR	<b>43C</b>
28.0K-Ohm	NRC06F2802TR	<b>44C</b>
28.7K-Ohm	NRC06F2872TR	<b>45C</b>
29.4K-Ohm	NRC06F2942TR	<b>46C</b>
30.1K-Ohm	NRC06F3012TR	<b>47C</b>
30.9K-Ohm	NRC06F3092TR	<b>48C</b>
31.6K-Ohm	NRC06F3162TR	<b>49C</b>
32.4K-Ohm	NRC06F3242TR	<b>50C</b>
33.2K-Ohm	NRC06F3322TR	<b>51C</b>
34.0K-Ohm	NRC06F3402TR	<b>52C</b>
34.8K-Ohm	NRC06F3482TR	<b>53C</b>
35.7K-Ohm	NRC06F3572TR	<b>54C</b>
36.6K-Ohm	NRC06F3652TR	<b>55C</b>
37.4K-Ohm	NRC06F3742TR	<b>56C</b>
38.3K-Ohm	NRC06F3832TR	<b>57C</b>
39.2K-Ohm	NRC06F3922TR	<b>58C</b>
40.2K-Ohm	NRC06F4022TR	<b>59C</b>
41.2K-Ohm	NRC06F4122TR	<b>60C</b>
42.2K-Ohm	NRC06F4222TR	<b>61C</b>
43.2K-Ohm	NRC06F4322TR	<b>62C</b>
44.2K-Ohm	NRC06F4422TR	<b>63C</b>
45.3K-Ohm	NRC06F4532TR	<b>64C</b>
46.4K-Ohm	NRC06F4642TR	<b>65C</b>
47.5K-Ohm	NRC06F4752TR	<b>66C</b>
48.7K-Ohm	NRC06F4872TR	<b>67C</b>
49.9K-Ohm	NRC06F4992TR	<b>68C</b>
51.1K-Ohm	NRC06F5112TR	<b>69C</b>
52.3K-Ohm	NRC06F5232TR	<b>70C</b>
53.6K-Ohm	NRC06F5362TR	<b>71C</b>
54.9K-Ohm	NRC06F5492TR	<b>72C</b>
56.2K-Ohm	NRC06F5622TR	<b>73C</b>
57.6K-Ohm	NRC06F5762TR	<b>74C</b>
59.0K-Ohm	NRC06F5902TR	<b>75C</b>
60.4K-Ohm	NRC06F6042TR	<b>76C</b>
61.9K-Ohm	NRC06F6192TR	<b>77C</b>
63.4K-Ohm	NRC06F6342TR	<b>78C</b>
64.9K-Ohm	NRC06F6492TR	<b>79C</b>
66.5K-Ohm	NRC06F6652TR	<b>80C</b>
68.1K-Ohm	NRC06F6812TR	<b>81C</b>
69.8K-Ohm	NRC06F6982TR	<b>82C</b>
71.5K-Ohm	NRC06F7152TR	<b>83C</b>
73.2K-Ohm	NRC06F7322TR	<b>84C</b>

**NIC COMPONENTS CORP.**[www.nicccomp.com](http://www.nicccomp.com)

75.0K-Ohm	NRC06F7502TR	<b>85C</b>
76.8K-Ohm	NRC06F7682TR	<b>86C</b>
78.7K-Ohm	NRC06F7872TR	<b>87C</b>
80.6K-Ohm	NRC06F8062TR	<b>88C</b>
82.5K-Ohm	NRC06F8252TR	<b>89C</b>
84.5K-Ohm	NRC06F8452TR	<b>90C</b>
86.6K-Ohm	NRC06F8662TR	<b>91C</b>
88.7K-Ohm	NRC06F8872TR	<b>92C</b>
90.9K-Ohm	NRC06F9092TR	<b>93C</b>
93.1K-Ohm	NRC06F9312TR	<b>94C</b>
95.3K-Ohm	NRC06F9532TR	<b>95C</b>
97.6K-Ohm	NRC06F9762TR	<b>96C</b>
100K-Ohm	NRC06F1003TR	<b>01D</b>
102K-Ohm	NRC06F1023TR	<b>02D</b>
105K-Ohm	NRC06F1053TR	<b>03D</b>
107K-Ohm	NRC06F1073TR	<b>04D</b>
110K-Ohm	NRC06F1103TR	<b>05D</b>
113K-Ohm	NRC06F1133TR	<b>06D</b>
115K-Ohm	NRC06F1153TR	<b>07D</b>
118K-Ohm	NRC06F1183TR	<b>08D</b>
121K-Ohm	NRC06F1213TR	<b>09D</b>
124K-Ohm	NRC06F1243TR	<b>10D</b>
127K-Ohm	NRC06F1273TR	<b>11D</b>
130K-Ohm	NRC06F1303TR	<b>12D</b>
133K-Ohm	NRC06F1333TR	<b>13D</b>
137K-Ohm	NRC06F1373TR	<b>14D</b>
140K-Ohm	NRC06F1403TR	<b>15D</b>
143K-Ohm	NRC06F1433TR	<b>16D</b>
147K-Ohm	NRC06F1473TR	<b>17D</b>
150K-Ohm	NRC06F1503TR	<b>18D</b>
154K-Ohm	NRC06F1543TR	<b>19D</b>
158K-Ohm	NRC06F1583TR	<b>20D</b>
162K-Ohm	NRC06F1623TR	<b>21D</b>
165K-Ohm	NRC06F1653TR	<b>22D</b>
169K-Ohm	NRC06F1693TR	<b>23D</b>
174K-Ohm	NRC06F1743TR	<b>24D</b>
178K-Ohm	NRC06F1783TR	<b>25D</b>
182K-Ohm	NRC06F1823TR	<b>26D</b>
187K-Ohm	NRC06F1873TR	<b>27D</b>
191K-Ohm	NRC06F1913TR	<b>28D</b>
196K-Ohm	NRC06F1963TR	<b>29D</b>
200K-Ohm	NRC06F2003TR	<b>30D</b>

**NIC COMPONENTS CORP.**[www.nicccomp.com](http://www.nicccomp.com)

205K-Ohm	NRC06F2053TR	<b>31D</b>
210K-Ohm	NRC06F2103TR	<b>32D</b>
215K-Ohm	NRC06F2153TR	<b>33D</b>
221K-Ohm	NRC06F2213TR	<b>34D</b>
226K-Ohm	NRC06F2263TR	<b>35D</b>
232K-Ohm	NRC06F2323TR	<b>36D</b>
237K-Ohm	NRC06F2373TR	<b>37D</b>
243K-Ohm	NRC06F2433TR	<b>38D</b>
249K-Ohm	NRC06F2493TR	<b>39D</b>
255K-Ohm	NRC06F2553TR	<b>40D</b>
261K-Ohm	NRC06F2613TR	<b>41D</b>
267K-Ohm	NRC06F2673TR	<b>42D</b>
274K-Ohm	NRC06F2743TR	<b>43D</b>
280K-Ohm	NRC06F2803TR	<b>44D</b>
287K-Ohm	NRC06F2873TR	<b>45D</b>
294K-Ohm	NRC06F2943TR	<b>46D</b>
301K-Ohm	NRC06F3013TR	<b>47D</b>
309K-Ohm	NRC06F3093TR	<b>48D</b>
316K-Ohm	NRC06F3163TR	<b>49D</b>
324K-Ohm	NRC06F3243TR	<b>50D</b>
332K-Ohm	NRC06F3323TR	<b>51D</b>
340K-Ohm	NRC06F3403TR	<b>52D</b>
348K-Ohm	NRC06F3483TR	<b>53D</b>
357K-Ohm	NRC06F3573TR	<b>54D</b>
366K-Ohm	NRC06F3653TR	<b>55D</b>
374K-Ohm	NRC06F3743TR	<b>56D</b>
383K-Ohm	NRC06F3833TR	<b>57D</b>
392K-Ohm	NRC06F3923TR	<b>58D</b>
402K-Ohm	NRC06F4023TR	<b>59D</b>
412K-Ohm	NRC06F4123TR	<b>60D</b>
422K-Ohm	NRC06F4223TR	<b>61D</b>
432K-Ohm	NRC06F4323TR	<b>62D</b>
442K-Ohm	NRC06F4423TR	<b>63D</b>
453K-Ohm	NRC06F4533TR	<b>64D</b>
464K-Ohm	NRC06F4643TR	<b>65D</b>
475K-Ohm	NRC06F4753TR	<b>66D</b>
487K-Ohm	NRC06F4873TR	<b>67D</b>
499K-Ohm	NRC06F4993TR	<b>68D</b>
511K-Ohm	NRC06F5113TR	<b>69D</b>
523K-Ohm	NRC06F5233TR	<b>70D</b>
536K-Ohm	NRC06F5363TR	<b>71D</b>
549K-Ohm	NRC06F5493TR	<b>72D</b>

**NIC COMPONENTS CORP.**[www.nicccomp.com](http://www.nicccomp.com)

562K-Ohm	NRC06F5623TR	<b>73D</b>
576K-Ohm	NRC06F5763TR	<b>74D</b>
590K-Ohm	NRC06F5903TR	<b>75D</b>
604K-Ohm	NRC06F6043TR	<b>76D</b>
619K-Ohm	NRC06F6193TR	<b>77D</b>
634K-Ohm	NRC06F6343TR	<b>78D</b>
649K-Ohm	NRC06F6493TR	<b>79D</b>
665K-Ohm	NRC06F6653TR	<b>80D</b>
681K-Ohm	NRC06F6813TR	<b>81D</b>
698K-Ohm	NRC06F6983TR	<b>82D</b>
715K-Ohm	NRC06F7153TR	<b>83D</b>
732K-Ohm	NRC06F7323TR	<b>84D</b>
750K-Ohm	NRC06F7503TR	<b>85D</b>
768K-Ohm	NRC06F7683TR	<b>86D</b>
787K-Ohm	NRC06F7873TR	<b>87D</b>
806K-Ohm	NRC06F8063TR	<b>88D</b>
825K-Ohm	NRC06F8253TR	<b>89D</b>
845K-Ohm	NRC06F8453TR	<b>90D</b>
866K-Ohm	NRC06F8663TR	<b>91D</b>
887K-Ohm	NRC06F8873TR	<b>92D</b>
909K-Ohm	NRC06F9093TR	<b>93D</b>
931K-Ohm	NRC06F9313TR	<b>94D</b>
953K-Ohm	NRC06F9533TR	<b>95D</b>
976K-Ohm	NRC06F9763TR	<b>96D</b>
1.0 Meg-Ohm	NRC06F1004TR	<b>01E</b>